SATCO NUVO





4" & 6" MODELS IN **ROUND & SQUARE**

STARFISH™ SMART ENABLED **PRODUCT**

> **SMOOTH BAFFLE REDUCES GLARE**

RGB, COLOR-CHANGING & TUNABLE WHITE

PRE-SET AND CUSTOM **EFFECTS**

SUGGESTED APPLICATIONS:

Residential, Multifamily, Commercial, Hospitality, Offices

LED SMART SLIMFIT DOWNLIGHTS

SMOOTH BAFFLE | REMOTE DRIVER



Millions of Colors

Warm to Cool Tunable White

SATCO|NUVO's LED Slimfit Downlights with STARFISH™ technology are the ultimate choice for smart lighting and ambiance control. Download the STARFISH™ app to customize any tunable white color temperatures from 2000K warm white light to 5000K natural light, or choose from millions of colors on the RGB spectrum, all from your mobile device. Offered in round and square with a smooth baffle to reduce glare, these slimfit downlights are ideal for transforming residential and multifamily environments.

These downlights are also compatible with Siri, Alexa, Google Home, and SmartThings so they can be easily incorporated into your smart home.

































LED SMART SLIMFIT DOWNLIGHTS

SMOOTH BAFFLE | REMOTE DRIVER

GENERAL SPECIFICATIONS

Input Voltage, Frequency: 120V, 60Hz **Power Factor, THD%:** >0.9, <30% Tunable White: 2000K-5000K CCT

RGB: Millions of Colors

Dimmable: Only with STARFISH™ App

CRI: 90

Efficacy: up to 62 LPW Beam Angle: 110°

Construction: Aluminum

Finish: White

Lens: Polycarbonate

Ambient Operating Temperature: -20°C (-4°F) to +40°C (+104°F)

Location Rating: Wet

IC Rating: Yes









ITEM SPECIFICATIONS / ORDER INFO

Item	Size	Shape	Lumens	Wattage	Incandescent Replacement Wattage	Input Current	Master Carton
S11564	4"	Round	540	9W	45W	0.08A	20
S11565	4"	Square	540	9W	45W	0.08A	20
S11566	6"	Round	750	12W	60W	0.10A	20
S11567	6"	Square	750	12W	60W	0.10A	20

OPTIONAL ACCESSORIES

Item	Description				
80-943	4'' Adjustable Rough-In Mounting Plate				
80-944	6" Adjustable Rough-In Mounting Plate				
80-950	4" Rough-In Mounting Plate				
80-951	6" Rough-In Mounting Plate				
80-946	4" Goof Ring				
80-947	6" Goof Ring				
80-986	6' Remote Driver Extension Cable				



4" & 6"Adjustable Rough-In Mounting Plates





6' Extension Cable





4" & 6"Rough-In Mounting Plates

4" & 6" Goof Rings

DIMENSIONS/WEIGHTS

Item	Diameter/ Width (A)	Length (B)	Height (C)	Weight
S11564	5.00"	•	1.25"	0.93 Lbs.
S11565	5.00"	5.00"	1.25"	1.04 Lbs.
S11566	7.17"	•	1.25"	1.19 Lbs.
S11567	7.13"	7.13"	1.25"	1.32 Lbs.









DOWNLOAD THE STARFISH APP



CONNECT Download the STARFISH™ app



INSTALL

Pair the smart downlights and configure your settings



ENJOY

The convenience and customization of smart lighting

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation

WARNING: Some products included in this specification sheet may be subject to the warning requirements of California's Proposition 65. Please refer to your product packaging for more information. Replacement wattage shown depends on application and fixture. Specifications are subject to change without prior notice.